






General technical specification

Mechanical and electrical design

Mounting arrangements

	Code/CodeII							Product code pos. 12
Foot-mounted motor.	IM B3 IM 1001	IM V5 IM 1011	IM V6 IM 1031	IM B6 IM 1051	IM B7 IM 1061	IM B8 IM 1071		A = foot-mounted, term.box top
								R = foot-mounted, term.box RHS
Flange-mounted motor, large flange	IM B5 IM 3001	IM V1 IM 3011	IM V3 IM 3031	*) IM 3051	*) IM 3061	*) IM 3071		L = foot-mounted, term.box LHS
								B = flange mounted, large flange
Flange-mounted motor, small flange	IM B14 IM 3601	IM V18 IM 3611	IM V19 IM 3631	*) IM 3651	*) IM 3661	*) IM 3671		C = flange mounted, small flange
								H = foot/flange-mounted, term.box top
Foot- and flange-mounted motor with feet, large flange	IM B35 IM 2001	IM V15 IM 2011	IM V36 IM 2031	*) IM 2051	*) IM 2061	*) IM 2071		S = foot/flange-mounted, term.box RHS
								T = foot/flange-mounted, term.box LHS
Foot- and flange-mounted motor with feet, small flange	IM B34 IM 2101	IM V17 IM 2111	IM 2131	IM 2151	IM 2161	IM 2171		J = foot/flange-mounted, small flange
								
Foot-mounted motor, shaft with free extensions	IM 1002	IM 1012	IM 1032	IM 1052	IM 1062	IM 1072		
								

*) Not stated in IEC 60034-7.

Note: In case of motors mounted with the shaft upwards and water or liquids are expected to go down along the shaft, the user must take care to mount some means capable of preventing it.